

# Automatic Digital Sound / Bell Timer Announcer

MODEL Name: The QCM-6200 Ver.G



## \*Application Places:

Government institutions, military units, schools, hospitals, companies, factories, department stores, markets, supermarkets, amusement parks...ect. Broadcast the music / bells / messages at fixed times.

## \*\* Feature & Specification:

- (1) **LCD** Display function can be shown in Chinese / English.
- (2) Built-in Memory based on **CF card** of Voice Module. Six melodies are installed as a standard while the tool software provided can help set 99 units of music / messages on your own.
- (3) Digital voice sampling frequency is to be possible up to **44.1KHz/16BITS**.
- (4) Provide 2 timer schedules (schedule A / schedule B). Each has **80** fixed timer schedules in the system in a day. Users may choose either of them and switch to operate.
- (5) Settings for different schedules from the days in a week are available.
- (6) Same schedule for each day is available.
- (7) Provide **5** specific date schedules and fixed timer outputs. Each specific date has **80** fixed timer groups.
- (8) Provide **7** groups of outputs with relay. Users could set and operate the schedule via LCD freely.
- (9) Provide **1** group relay output active ahead of fixed time audio output. It could match the **PA** system action.
- (10) All schedules can be operated and set from the LCD front panel keypad.
- (11) The relay outputs and melody performances could be operated **manually** or **automatically**.
- (12) If system power failures, the contents could be hold.
- (13) It displays current date and time when in standby mode.
- (14) Connect PC with **RS-232 interface**. Then Use tool software to edit schedules, downloading information and time synchronously.
- (15) The volume for audio output in each schedule is adjustable.
- (16) External GPS module (optional)



HWAN MAW TECH. Co., Ltd.  
E-mail : hmtsales@hmt.com.tw  
TEL: 886-2-2274-1347