

## Digital Sound / Bell Timer Announcer

MODEL Name: QCM-6200 VER. GS



### \*APPLICATIONS\*

Government institutions, military units, schools, hospitals, companies, factories, department stores, markets, supermarkets, amusement parks...etc. Broadcast the music / bells / announcements at fixed times.

### \*\*FEATURE & SPECIFICATION\*\*\*

- (1) Fully **LCD** display in Chinese/Mandarin. With voice broadcast function
- (2) Support PC Monitor Software for controlling schedules, relay outputs and announcements instantly *New!*
- (3) Built-in a **CF Memory Card**. Six melodies are installed in it as a standard while the tool software provided can help set 99 units of music / messages
- (4) Digital voice sampling frequency can be up to **44.1KHz/16 BITS**
- (5) Up to 80 schedules can be set freely for each day
- (6) Connect PC with **RS-232 interface wire**. Then operate tool software to edit schedules, download data and synchronize time
- (7) **The volume for audio output in each schedule is adjustable**
- (8) Settings for different / same schedules on each weekday are available
- (9) Provide A / B schedule groups for setting via the LCD front panel / data downloading
- (10) Provide extra five special days in schedule settings. Each has 80 available schedules
- (11) Provide seven relay output pins for programming
- (12) Provide **one relay output pin** to be triggered for starting an outer amplifier
- (13) All schedules can be operated and set from the LCD front panel
- (14) Output pins and melody performances could be operated manually or automatically
- (15) The schedules and calendar can be hold if power failure
- (16) The LCD front panel displays the current date and time when in standby mode
- (17) Optional Equipment : external GPS module for auto time synchronization

(Please contact the Sales Dept.)



Hwan Maw Tech. Co., Ltd  
TEL: 886-2-2274-1347  
FAX: 886-2-2273-3014